

BLDC Motors (Speed Control & Applications in Robotics)

Nikita Navnath Magdum¹, Vaibhavi Shankar Nalwade², Sakshi Gurudatta Kamble³

1. *Electrical Engineering, Nanasaheb Mahadik College of Engineering*

2. *Electrical Engineering, Nanasaheb Mahadik College of Engineering*

3. *Electrical Engineering, Nanasaheb Mahadik College of Engineering*

Abstract - Brushless DC (BLDC) motors are rapidly replacing conventional brushed DC motors across various industrial and consumer applications due to their superior torque-to-weight ratio, high efficiency, and operational reliability. This report provides a comprehensive review of BLDC motor technology, detailing its fundamental operating principles, inverter-driven electronic commutation techniques, and system dynamics. Key research focuses include the implementation of sensorless control strategies to minimize hardware cost and complexity, alongside the optimization of speed control utilizing Proportional-Integral-Derivative (PID) and Field-Oriented Control (FOC) algorithms. Furthermore, this work evaluates the resulting efficiency gains and presents a detailed, simulation-based performance analysis conducted within the MATLAB/Simulink environment.

Keywords: - Brushless DC motors focus on their electronic commutation, lack of brushes, and high-efficiency performance.

1. INTRODUCTION

The rapid advancement of industrial automation, electric mobility, and robotics requires actuators that deliver high power density, rapid dynamic response, and low maintenance overhead. Traditionally, brushed permanent magnet DC motors dominated these fields due to their straightforward, linear control characteristics. However, mechanical brushed commutation introduces significant drawbacks, including continuous friction, mechanical wear, electrical arcing, and thermal dissipation limits on the rotor. These issues restrict maximum operational speeds and degrade system reliability over time.

The integration of solid-state power electronics solved these issues through the development of the Brushless DC (BLDC) motor. By fundamentally inverting the mechanical arrangement—placing permanent magnets on the moving rotor and the copper phase windings on the stationary stator—the need for physical brushes is entirely eliminated.



Internal architecture of a BLDC motor showcasing the stationary stator windings and permanent magnet rotor core. Source: Bosca78 / Getty Images

2. Operating Principles & Electronic Commutation

BLDC motors are synchronous motors, meaning the magnetic field generated by the stator and the magnetic field of the rotor rotate at the exact same frequency. Because mechanical brushes are absent, commutation—the process of switching current through the phases to generate continuous rotation—must be handled electronically.

This process is handled by a three-phase inverter bridge consisting of six power switching devices, such as MOSFETs or IGBTs. The switches are systematically toggled based on the instantaneous position of the rotor. To keep the motor spinning, the stator windings are energized in a specific six-step sequence (trapezoidal commutation). Every 60 electrical degrees, the controller switches the active phases to ensure that the stator's magnetic field maintains a 90-degree displacement relative to the rotor magnets, maximizing torque production.

3. Advanced Speed Control Architectures

Achieving precise speed regulation under varying mechanical loads requires closed-loop control feedback. The performance profile of the system is largely determined by the chosen control strategy:

3.1 Proportional-Integral-Derivative (PID) Control

The classical PID controller remains widely used due to its structural simplicity and ease of implementation. In a speed-controlled loop, the controller calculates an error value as the difference between a measured speed and a desired setpoint. The PID algorithm adjusts the Pulse Width Modulation (PWM) duty cycle fed to the inverter gates to correct the error. While effective for steady-state tracking, traditional PID parameters can struggle during rapid, non-linear load transitions.

3.2 Field-Oriented Control (FOC)

For applications demanding smooth torque and exceptional dynamic responsiveness, Field-Oriented Control (FOC) is utilized. FOC transforms the three-phase time and position-dependent stator currents (I_a , I_b , I_c) into a two-coordinate time-invariant system (I_d , I_q) using mathematical transformations (Clarke and Park transforms).

- Direct Axis Current (I_d): Aligned with the rotor flux, controlled to zero to prevent demagnetization and minimize power waste.
- Quadrature Axis Current (I_q): Perpendicular to the rotor flux, directly proportional to electromagnetic torque.

By decoupling torque and flux control, FOC allows the BLDC motor to behave like a highly responsive brushed motor, virtually eliminating torque ripple and maximizing efficiency across all speed ranges.

4. Sensored vs. Sensorless Paradigms

Historically, rotor position tracking relied heavily on three internal Hall-effect sensors embedded in the stator, which detect magnetic transitions. While reliable, these sensors add manufacturing costs, increase wiring complexity, and introduce failure points in harsh, high-temperature, or corrosive industrial environments.

Modern research focuses heavily on sensorless control techniques. Instead of physical hardware, digital signal processors use mathematical models to observe the motor's operating states. The most prominent method monitors Back-EMF (Back-EMF). When the permanent magnets move past the unenergized phase winding during the six-step sequence, they induce a voltage waveform. By detecting the point where this voltage crosses zero (Zero Crossing Detection), the controller determines the exact position of the rotor.

5. Simulation Methodology: MATLAB/Simulink

To validate these control algorithms before deploying them to physical hardware, engineering workflows rely on simulation platforms. Using MATLAB/Simulink, a mathematical model of the entire electromechanical

system can be constructed. The simulation environment includes:

1. The BLDC Motor Model: Governed by state-space equations representing stator resistance (R_s), phase inductance (L_s), and back-EMF constants.
2. The Inverter Circuit: Modeling the switching characteristics of the power semiconductors.
3. The Control Loop: Implementing either the PWM-driven PID blocks or the coordinate-transform blocks required for FOC.

Through Simulink, researchers can subject the virtual motor to step changes in reference speed or abrupt load disturbances. This enables precise tuning of controller gains, measurement of settling times, and quantification of efficiency gains—all while protecting physical components from overcurrent conditions during development.

6. Current Challenges in BLDC Motor Systems

Despite their significant advantages over brushed alternatives, the widespread deployment of BLDC motors—particularly in high-precision robotics and rugged industrial environments—is limited by several distinct technical hurdles

6.1. Torque Ripple and Acoustic Noise

In standard trapezoidal commutation, switching currents between the stator phases causes rapid fluctuations in the magnetic field. This phenomenon, known as torque ripple, leads to microscopic vibrations along the motor shaft. In robotics, torque ripple compromises precision during ultra-slow movements (such as surgical or robotic welding arms) and generates significant acoustic high-frequency noise, which is highly undesirable in consumer electronics and electric vehicles.

6.2. The "Zero-Speed" Problem in Sensorless Control

While sensorless control (eliminating Hall-effect sensors) reduces hardware costs and points of failure, it introduces a major startup problem. Sensorless algorithms rely on measuring Back-EMF to determine rotor position. However, Back-EMF is directly proportional to motor speed ($E_b \propto \omega$).

- When the motor is stationary or turning at ultra-low speeds, the Back-EMF signal drops to near zero, making it impossible for the controller to accurately detect where the rotor is.
- As a result, starting a sensorless BLDC motor requires an open-loop "blind kick" strategy, which can cause temporary backward rotation or stalling under heavy mechanical loads.

6.3. Computational Overhead and Thermal Management

Advanced control algorithms like Field-Oriented Control (FOC) require rapid mathematical transformations (Clarke/Park transforms) executed at kilohertz frequencies. This necessitates expensive, high-performance microcontrollers or Digital Signal Processors (DSPs). Additionally, operating at high switching frequencies increases switching losses within the inverter's MOSFETs/IGBTs, generating substantial heat that requires robust thermal management systems.

7. CONCLUSIONS

This report has provided a thorough investigation into Brushless DC (BLDC) motor technology, evaluating its core design principles, control methodologies, and its pivotal role in advancing modern automation and robotics systems. By replacing mechanical brushes with an inverter-driven electronic commutation bridge, BLDC motors effectively overcome the physical limitations of friction, thermal constraints, and wear that plague traditional brushed DC actuators. This makes them highly dependable, efficient components capable of meeting rigorous industrial demands.

REFERENCES

1. Carey, K. D., Zimmerman, N., & Ababei, C. (2019). Hybrid field oriented and direct torque control for sensorless BLDC motors used in aerial drones. *IET Power Electronics*, 12(15), 438–449. <https://doi.org/10.1049/iet-pel.2018.5231>

Cited by: 60

2. Lad, C. K., & Chudamani, R. (2013). Sensorless brushless DC motor drive based on commutation instants derived from the line voltages and line voltage differences. In *2013 Annual IEEE India Conference (INDICON)* (pp. 1–5). IEEE. <https://doi.org/10.1109/indcon.2013.6725855>

Cited by: 8

3. Padilla-García, E. A., Cervantes-Culebro, H., Rodríguez-Angeles, A., & Cruz-Villar, C.A. (2023). Selection/control concurrent optimization of BLDC motors for industrial robots. *PLOS ONE*, 18(8), e0289717. <https://doi.org/10.1371/journal.pone.0289717>

Cited by: 12

4. Sawant, D. S., Rao, Y. S., & Sawant, R. R. (2023). Sensorless control of a BLDC motor using Back-EMF detection method. In *2023 International Conference for Advancement in Technology (ICONAT)* (pp. 1–5). IEEE. <https://doi.org/10.1109/iconat57137.2023.10079963>

Cited by: 7

5. Syamsiana, I. N., Wang, M. S., Aripriharta, & Firmansah, A. (2019). A study of sliding mode observer sensorless of brushless motor using Embedded Coder Matlab/Simulink. In *2019 International Conference on Electrical, Electronics and Information Engineering (ICEEIE)* (pp. 1–6). IEEE. <https://doi.org/10.1109/iceeie47180.2019.8981456>

Cited by: 7