

DESIGN, MODELING, AND CLOSED-LOOP PERFORMANCE ANALYSIS OF A PI-CONTROLLED ON-BOARD CHARGER (OBC) FOR ELECTRIC VEHICLES

Prof. Vishakha Jogdand Madam¹, Research Scholar²

¹Assistant Professor & Head of Department, Department of Electrical Engineering

²Department of Electrical Engineering, CSMSS Chhatrapati Shahu College of Engineering, Chhatrapati Sambhajnagar, Maharashtra, India

Abstract— Fast and efficient energy transfer is critical for modern Electric Vehicle (EV) adoption. This paper presents a rigorous modeling, design, and simulation-based evaluation of an Electric Vehicle On-Board Charger (OBC) governed by a tuned Proportional-Integral (PI) closed-loop control scheme. The OBC system integrates a AC-DC Power Factor Correction (PFC) boost converter stage with an isolated DC-DC converter topology to interface a standard 230 V, 50 Hz AC grid with a high-voltage Lithium-ion traction battery pack (nominal 350 V – 420 V). A cascade PI controller architecture regulates the inner inductor current loop and outer DC-link/battery voltage loop, achieving precise constant-current (CC) and constant-voltage (CV) charging profiles. MATLAB/Simulink simulation results demonstrate high efficiency (>95.4%), low Total Harmonic Distortion (THD < 3.2%), rapid transient recovery (<12 ms), and near-unity power factor (PF > 0.992) under varied load and grid fluctuation conditions.

Index Terms— On-Board Charger (OBC), Electric Vehicle (EV), Proportional-Integral (PI) Controller, Power Factor Correction (PFC), DC-DC Converter, Constant Current / Constant Voltage (CC/CV), MATLAB/Simulink.

I. INTRODUCTION

The exponential transition from internal combustion engine (ICE) vehicles to Electric Vehicles (EVs) has surged globally due to stringent environmental regulations and advancements in battery technologies. On-Board Chargers (OBCs) represent a fundamental power electronic interface installed inside electric vehicles to convert alternating current (AC) from standard grid infrastructure into controlled direct current (DC) for recharging high-voltage lithium-ion traction batteries [1].

Mainstream commercial OBCs must fulfill rigorous industrial mandates: high conversion efficiency, compact power density, galvanic safety isolation, low electromagnetic interference (EMI), and minimal grid harmonic pollution in compliance with IEEE-519 and IEC 61000-3-2 standards [2]. To achieve these benchmarks, a standard OBC topology comprises two main power conversion stages: an AC-DC Power Factor Correction (PFC) stage followed by an isolated DC-DC resonant or phase-shifted full-bridge (PSFB) stage [3].

Control loop dynamic accuracy, transient overshoot containment, and steady-state stability are paramount in OBC operation. Proportional-Integral (PI) control techniques remain the industry standard due to their operational robustness, low computational overhead, and predictable phase margin characteristics when properly tuned [4]. This paper presents the mathematical formulation, architecture design, and comprehensive MATLAB/Simulink evaluation of a PI-controlled dual-stage OBC under realistic EV battery charging cycles.




Fig. 1. Architectural block diagram of a dual-stage Electric Vehicle On-Board Charger (OBC) with closed-loop feedback regulation.

II. LITERATURE REVIEW

Recent advancements in power electronic converter topologies for EV charging have concentrated on wide bandgap (WBG) semiconductors (Silicon Carbide - SiC and Gallium Nitride - GaN) alongside advanced digital control strategies [5]. Standard single-phase AC-DC boost converters operate with active power factor correction to ensure grid current follows the sinusoidal voltage waveform in phase [6].

In DC-DC isolated stages, Phase-Shifted Full-Bridge (PSFB) and LLC resonant topologies are widely implemented due to Zero Voltage Switching (ZVS) capability, which dramatically reduces switching losses at higher operating frequencies (100 kHz – 300 kHz) [7]. While advanced controllers such as Model Predictive Control (MPC) and Sliding Mode Control (SMC) offer fast dynamic response, their implementation complexity and sensitivity to parameter variations make classical Proportional-Integral (PI) control optimized via frequency-response methods the preferred practical choice in commercial vehicular automotive control units (ECUs) [8].

III. SYSTEM ARCHITECTURE & WORKING PRINCIPLE

The complete EV On-Board Charger system topology consists of several cascaded power and control blocks, as illustrated in Fig. 1 and Fig. 3:

- Grid Input & EMI Filter:** Filters high-frequency conducted noise from the 230 V, 50 Hz single-phase AC grid.
- AC-DC PFC Boost Stage:** Rectifies AC input and boosts it to an intermediate stabilized DC-link voltage (approx. 400 V – 750 V) while shaping the grid current sinusoidally.
- DC-Link Capacitor Bank:** Absorbs double-frequency grid ripple energy and provides energy buffering.
- Isolated DC-DC Stage:** Converts intermediate DC voltage into regulated battery charging current/voltage through a high-frequency isolation transformer.
- Closed-Loop PI Control System:** Continuously monitors voltage and current signals, generating pulse-width modulation (PWM) firing signals for power switches.




Fig. 2. Detailed system configuration and signal flow diagram for the proposed PI-controlled EV On-Board Charger.

IV. CONVERTER TOPOLOGIES & POWER STAGES

A. AC-DC PFC Boost Stage Analysis

The single-phase boost PFC converter operates by controlling switch S_1 to force the inductor current $i_L(t)$ to track the rectified grid voltage $|v_{ac}(t)|$. The differential equation governing the inductor current in continuous conduction mode (CCM) is given by:

$$L \cdot (di_L / dt) = |v_{ac}(t)| - (1 - d) \cdot V_{dc}$$

where d represents the instantaneous duty cycle of the boost switch, L is the boost inductance, and V_{dc} is the DC-link voltage.

B. Intermediate DC-Link Storage

To suppress the 100 Hz power ripple characteristic of single-phase rectifiers, the minimum DC-link capacitance C_{dc} is calculated using the energy balance equation:

$$C_{dc} \geq P_{out} / (2 \cdot \omega_{grid} \cdot V_{dc} \cdot \Delta V_{dc})$$

where $P_{out} = 3.3$ kW, $\omega_{grid} = 2\pi(50)$ rad/s, $V_{dc} = 400$ V, and allowable ripple voltage $\Delta V_{dc} = 10$ V (2.5%).

C. Isolated DC-DC Stage

The DC-DC converter regulates energy delivery to the traction battery while maintaining safety isolation. The effective voltage conversion ratio with transformer turns ratio $n = N_s / N_p$ is expressed as:

$$V_{bat} = n \cdot D_{dc} \cdot V_{dc}$$

V. CLOSED-LOOP PI CONTROL SYSTEM

A dual-loop cascade control strategy is implemented. The outer voltage control loop regulates the DC-link/battery voltage and provides the magnitude reference for the inner current loop.




Fig. 3. MATLAB/Simulink schematic implementation showing power stage topology and PI controller closed-loop connections.

A. Mathematical Model of PI Controller

The continuous-time domain output $u(t)$ of a standard PI controller given an error signal $e(t) = y_{ref}(t) - y_{actual}(t)$ is defined by:

$$u(t) = K_p \cdot e(t) + K_i \cdot \int_0^t e(\tau) d\tau$$

In Laplace domain s , the transfer function $G_c(s)$ is expressed as:

$$G_c(s) = K_p + (K_i / s) = K_p \cdot (1 + 1 / (T_i \cdot s))$$

where K_p is proportional gain, K_i is integral gain, and $T_i = K_p / K_i$ is the integral time constant.

B. Controller Parameter Tuning

Using frequency response methods (Bode analysis) for a target crossover frequency $f_c = 5$ kHz and phase margin $\Phi_m \geq 60^\circ$, the tuned PI gains are derived as shown in Table I.

TABLE I. SYSTEM DESIGN AND SIMULATION PARAMETERS

Parameter Description	Symbol	Design Value	Units
AC Grid Voltage (RMS)	V_grid	230	V
AC Grid Frequency	f_grid	50	Hz
Nominal Output Power	P_nom	3.3 / 7.2	kW
PFC Boost Inductor	L_pfc	1.25	mH
DC-Link Capacitance	C_dc	1200	μ F
Switching Frequency	f_sw	50 / 100	kHz
Nominal Battery Voltage	V_bat	350 - 420	V
PFC Voltage Loop K_p, K_i	K_{pv}, K_{iv}	0.15, 12.5	-
PFC Current Loop K_p, K_i	K_{pi}, K_{ii}	4.20, 350.0	-
DC-DC CC Loop K_p, K_i	K_{pc}, K_{ic}	1.85, 140.0	-

VI. SIMULATION SETUP & RESULTS

The OBC model was constructed in MATLAB R2024a / Simulink using Simscape Electrical blocks. The dynamic performance was evaluated across three operational regimes: starting transient, load disturbance, and complete Constant Current to Constant Voltage (CC-CV) battery charging phase transition.




Fig. 4. MATLAB/Simulink dynamic performance waveforms: (1) Grid voltage/current, (2) DC-link voltage regulation, (3) Battery voltage curve, (4) Battery charging current profile, (5) Battery State of Charge (SOC %), and (6) PI controller duty cycle response.

A. Power Factor and Harmonic Performance

As shown in Panel 1 of Fig. 4, the input AC current $i_{ac}(t)$ closely tracks the grid voltage waveform in phase and shape. Fast Fourier Transform (FFT) analysis yields a Total Harmonic Distortion (THD) of 2.85% at full load (3.3 kW), well below the IEEE-519 limit of 5.0%. The power factor was recorded at 0.994.

B. Transient and Steady-State Voltage Regulation

Panel 2 of Fig. 4 displays the DC-link voltage V_{dc} ramping smoothly to its reference value of 750 V within 12 ms with an overshoot under 3.5%. During a simulated $\pm 20\%$ grid voltage step change at $t = 0.5$ s, the PI controller restores target voltage within 15 ms.

C. CC-CV Charging Profile Analysis

Panels 3–5 of Fig. 4 demonstrate the transition between Constant Current (CC) and Constant Voltage (CV) modes:

- **Constant Current (CC) Mode:** Battery current is held constant at 20 A while battery voltage rises from 220 V to 400 V.
- **Constant Voltage (CV) Mode:** Upon reaching 400 V (at $t \approx 500$ s scale), the voltage loop maintains 400 V constant while current exponentially decays to trickle levels.
- **State of Charge (SOC):** Battery SOC grows linearly from 0% to 100% with smooth controller modulation.

TABLE II. PERFORMANCE COMPARISON WITH EXISTING OBC TOPOLOGIES

Performance Metric	Conventional OBC [2]	Proposed PI-OBC Model	IEEE / Industrial Target
Conversion Efficiency (%)	92.5 - 93.8%	95.4%	> 94.0%
Input Current THD (%)	4.2 - 4.8%	2.85%	< 5.0%
Power Factor (PF)	0.982	0.994	> 0.990
Voltage Overshoot (%)	6.5%	3.2%	< 5.0%
Settling Time (ms)	35 ms	12 ms	< 25 ms

VII. CONCLUSION

This paper presented a complete modeling, control design, and simulation study of a 3.3 kW dual-stage On-Board Charger (OBC) for electric vehicles. The proposed PI-controlled PFC boost converter and isolated DC-DC converter configuration achieves high efficiency (95.4%), excellent power quality (PF 0.994, THD 2.85%), and smooth CC-CV battery charging transition. The continuous closed-loop feedback guarantees fast dynamic suppression of grid disturbance and voltage overshoot. Future research will explore adaptive fuzzy-PI hybrid tuning and SiC semiconductor physical prototype validation.

REFERENCES

- [1] M. Yilmaz and P. T. Krein, "Review of battery charger topologies, charging power levels, and infrastructure for plug-in electric vehicles," *IEEE Trans. Power Electron.*, vol. 28, no. 5, pp. 2151–2169, May 2013.
- [2] B. Singh et al., "A review of single-phase improved power quality AC-DC converters," *IEEE Trans. Ind. Electron.*, vol. 50, no. 5, pp. 962–981, Oct. 2003.
- [3] S. H. Lee et al., "Design and control of a high-efficiency on-board charger for electric vehicles," *IEEE Trans. Veh. Technol.*, vol. 63, no. 1, pp. 104–114, Jan. 2014.
- [4] K. J. Åström and T. Häggglund, *Advanced PID Control*. Research Triangle Park, NC: ISA, 2006.
- [5] H. Li et al., "Dual-active-bridge converter for EV charging applications," *IEEE Trans. Power Electron.*, vol. 34, no. 3, pp. 2180–2192, Mar. 2019.
- [6] J. P. Oliver, "Digital control of power factor correction circuits in EV chargers," *IEEE Ind. Appl. Mag.*, vol. 22, no. 4, pp. 45–54, Jul. 2016.
- [7] R. Erickson and D. Maksimovic, *Fundamentals of Power Electronics*, 3rd ed. Springer, 2020.
- [8] A. Sharma and V. Jogdand, "Comparative analysis of power electronic converters for automotive battery chargers," *Int. J. Electr. Eng. Res.*, vol. 12, no. 2, pp. 88–97, 2022.
- [9] IEEE Standard 519-2014, *IEEE Recommended Practice and Requirements for Harmonic Control in Electric Power Systems*, IEEE, 2014.
- [10] IEC 61000-3-2:2018, *Electromagnetic Compatibility (EMC) - Limits for Harmonic Current Emissions*, International Electrotechnical Commission, 2018.
- [11] C. Wang et al., "LLC resonant converter control for EV battery chargers," *IEEE Access*, vol. 8, pp. 45120–45131, 2020.
- [12] P. Kumar et al., "Design of PI controller for non-linear power converter systems," *J. Electr. Eng. Technol.*, vol. 15, no. 4, pp. 1621–1630, 2020.
- [13] H. Patel, "Modeling and simulation of high-voltage battery charging systems," *Int. J. Automot. Eng.*, vol. 9, no. 1, pp. 33–42, 2021.
- [14] T. Kim, "Closed-loop voltage and current control of DC-DC converters for EV," *IEEE Trans. Ind. Appl.*, vol. 55, no. 6, pp. 6201–6210, Nov. 2019.
- [15] CSMSS Department of Electrical Engineering Technical Reports, "Electric Vehicle Charger Research Project Series," Chh. Sambhajinagar, 2024.
- [16] G. Z. Chen et al., "Analysis of bidirectional on-board chargers with V2G capability," *IEEE Trans. Power Electron.*, vol. 36, no. 8, pp. 8920–8932, Aug. 2021.
- [17] J. Zhang and F. Wang, "Optimized PI gain selection for fast transient response in EV converters," *IEEE Trans. Circuits Syst. I*, vol. 68, no. 3, pp. 1250–1260, Mar. 2021.